


Cree LED ground spotlight Sintra | warm-white | 3 watts | round | 1-light | 24 volt

## Product Images



## Short Description

---

The Cree LED ground spot Sintra is suitable for illuminating a path or driveway. The spotlight has 1 opening through which light shines, consumes 3 watts and runs on 24 volts.

## Description

---

The Cree LED Sintra ground light creates with its warm white light colour (2700k) and light angle of 30° an atmospheric view in your garden. The Sintra ground light is energy-efficient, environmentally friendly and uses only 3 watts. The ground light is made of stainless steel and has an IP value of 67 (IP-67). IP-67 means that the Sintra ground light is dust-proof and resistant to splash and spray water. The housing of this ground light is provided with a notch for the cable. This prevents the cable from being crushed under the ground. The cable that is attached to the ground light is 1 metre long and is equipped with a 24-volt connector.

The Sintra LED ground light is part of the 24-volt garden lighting system. This means that you can easily connect this ground light with other ground lights, but also with the other 24-volt garden lighting. For the operation of this ground light, you need a 24-volt transformer. You can choose from the LED transformer 24 volt or the LED transformer Astro 24 volt. The 24-volt LED transformer ensures that the incoming 230 volts are converted to low voltage (24 volts). The Astro LED transformer 24 Volt also does this, but this transformer can be programmed to 5 different positions and can be used to control the lighting. You can connect up to 80 Watts of different types of 24-volt garden lighting to both transformers (depends on which transformer you choose). The transformers are not supplied as standard, so if you do not already have a 24-volt transformer, you must add one of the two transformers to your shopping basket.

You can (have) this ground spotlight operated in several ways. This can be done in the following ways:

- With the Astro transformer
- Moon remote control
- Push dimmer / Remote control Novex
- App

To control the spotlights with the Moon, Novex and/or op, you need to purchase the wifi garden LED receiver. With the purchase of this receiver, you get free access to the app, which allows you to control the ground spotlight.

With 24-volt extension cables and 24-volt cable connectors, you can connect multiple Sintra ground lights with our other 24-volt garden lights. These accessories must be ordered separately from our webshop.

Tip: The wiring of 24-volt lights can be hidden under a layer of sand and does not have to be placed 60 cm under the ground.

When ordering the Cree LED Sintra ground light, you will receive a 5-year warranty. Would you like more information about this ground light? Read all product specifications or contact our LED specialists.

## Additional Information

---

Article number	L2352
EAN code	7435828594593
Brand	Hamulight
Suitable for	Outside
Light color	Warm white (2700K)
Input voltage	24V DC
LED chip	Cree
Consumption	3 watt
Dimmable	No
Lumen per LED (including lens)	145 lm
Color Rendering Index (CRI)	>82
Light angle	30 Degrees
Diameter	78 mm
Height	130 mm
Cabling per LED	100 cm
Transformer required?	No
Material	Stainless steel
Housing color	Nickel
IP value	IP67
Quality mark	CE, Rohs
Warranty	5 years
Energy label old	A++
Energy label new	G